

Firmware update over air (FWU)

1. TFTP firmware server, create directory "DECT4024" at same root as "Beatus" directory.
2. Copy Repeater firmware "DECT4024_Vxxxx.fwu" to directory "DECT4024"

ftp://10.1.24.101/FwuPath/

| Name | Size | Type | Modified |
|----------|------|-------------|------------------|
| Beatus | | File Folder | 16/01/2012 16:26 |
| DECT4024 | | File Folder | 06/01/2012 13:48 |

| Name | Size | Type | Modified |
|--------------------|--------|----------|------------------|
| DECT4024_v0010.fwu | 167 KB | FWU File | 06/01/2012 13:47 |

3. Select page "Firmware Update"
4. Set "Firmware update server address" and "Firmware path" according to TFTP server installation.
5. Type "DECT4024" firmware version.
6. Press "Save"

SME VoIP

Home / Status
Extensions
Servers
Network
Management
Firmware Update
Time
Country
Web Security
Central Directory

Firmware Update Settings

Firmware update server address: 10.1.24.101
Firmware path: /FwuPath

| Type | Required Version |
|--------------------|------------------|
| UXP1240H HW ver 00 | 0 |
| UXP1240H | 0 |
| 8630 | 0 |
| DECT4024 | 15 |
| UXP1240H | 0 |

Save

7. Select page "Repeaters"
8. Select "Refresh" (Update FWU progress and FW Info)

[Refresh](#)

| Idx | RPN | IPEI | DECT sync source | DECT sync mode | State | FW Info | FWU Progress |
|----------------------------|-------|----------------|------------------|-------------------|---------------|---------|--------------|
| <input type="checkbox"/> 0 | RPN01 | 00:5A:D8:5E:40 | RPN00 (-26dBm) | Local Automatical | Present@RPN00 | 14 | 43% |

After approx. 20 minutes FWU reached 100% and repeater reboots with new firmware version and progress complete. FWU several repeaters in parallel will take more minutes (Avoid radio interference, place repeaters with min. 1m apart)

| Idx | RPN | IPEI | DECT sync source | DECT sync mode | State | FW Info | FWU Progress |
|----------------------------|-------|----------------|------------------|-------------------|---------------|---------|--------------|
| <input type="checkbox"/> 0 | RPN01 | 00:5A:D8:5E:40 | RPN00 (-26dBm) | Local Automatical | Present@RPN00 | 15 | Complete |